

BIAS CURRENT VALUE TABLE

KENWOOD

| MODEL | BIAS CURRENT | MODEL | BIAS CURRENT |
|----------|--------------------|-----------|-------------------------|
| A-7 | FIXED | KR-65L | FIXED (40mA) |
| A-9 | 30mA | KR-90 | FIXED (20mA-100mA) |
| A-9D | 30mA | KR-90L | FIXED (20mA-100mA) |
| BASIC M1 | 20mA-40mA | KR-810 | NON ADJUST |
| BASIC M2 | 40mA | KR-820 | FIXED |
| KA-5X | 20mA | KR-820L | FIXED |
| KA-7X | 20mA-40mA | KR-830 | FIXED |
| KA-9X | 20mA | KR-845G | FIXED |
| KA-31 | FIXED | KR-850 | 50mA |
| KA-31G | FIXED | KR-865G | 50mA |
| KA-33 | FIXED | KR-910 | FIXED (40mA) |
| KA-51 | FIXED | KR-910L | FIXED (40mA) |
| KA-55 | FIXED (10mA-100mA) | KR-920 | FIXED |
| KA-71 | 30mA | KR-920L | FIXED |
| KA-77 | 30mA | KR-930 | 50mA (both X05 and X09) |
| KA-100 | FIXED (100mA) | KR-950 | 50mA |
| KA-311 | FIXED | KS-50 | NON ADJUST |
| KA-470 | NON ADJUST | KVA-503 | 50mA |
| KA-511 | FIXED | KVR-510 | FIXED (30mA-100mA) |
| KA-555 | FIXED (10mA-100mA) | KVR-970B | 50mA |
| KA-670 | NON ADJUST | KVR-970BP | 50mA |
| KA-770 | 30mA | L-02A | 50mA |
| KA-990 | 30mA | R-5D | NON ADJUST |
| KA-2200 | 40mA | R-5DL | NON ADJUST |
| KR-65 | FIXED (40mA) | | |

| MODEL | BIAS CURRENT | MODEL | BIAS CURRENT |
|--------------|---------------------|--------------|---------------------|
| A-5G | FIXED (5 – 100mA) | KA-880SD | 20mA |
| A-5S | FIXED (10 – 90mA) | KA-949 | 20mA |
| A-7G | 30mA | KA-990SD | 30mA |
| A-7S | FIXED (10 – 90mA) | KA-990V | 20mA |
| BASIC M1A | 20mA | KA-1100SD | 20mA |
| BASIC M2A | 40mA | KR-A10/L | NON-ADJUST |
| KA-32 | FIXED (50mA) | KR-A20 | NON-ADJUST |
| KA-34 | NON-ADJUST | KR-A30/L | 40mA |
| KA-44 | 50mA | KR-A50 | 40mA |
| KA-52 | 40mA | KR-A70 | 40mA |
| KA-54 | 50mA | KVR-A50 | 40mA |
| KA-72 | 40mA | KVR-A70R | 40mA |
| KA-74 | 50mA | KVR-A90R | 40mA |
| KA-92B | 30mA | RX-5 | NON-ADJUST |
| KA-94 | 20mA | RX-8 | NON-ADJUST |
| KA-660 | 30mA | | |
| KA-727 | 50mA | | |
| KA-747 | 30mA | | |
| KA-828 | 45mA | | |

BIAS-CURRENT VALUE TABLE

| MODEL | BIAS CURRENT | MODEL | BIAS CURRENT |
|----------|--------------|------------|--------------|
| KA-2000A | 30 mA | KR-8140 | 15 mA |
| KA-2002 | 20 mA | KR-8340 | 30 mA |
| KA-2002A | 20 mA | KR-9340 | 50 mA |
| KA-2600 | 20 mA | | |
| KA-3004 | 20 mA | KSQ-400 | 20 mA |
| KA-3344 | 20 mA | | |
| KA-4002 | 20 mA | MA-5100 | 20 mA |
| KA-4004 | 10 mA | MODEL-700M | 50 mA |
| KA-5002 | 30 mA | | |
| KA-6004 | 10 mA | | |
| KA-7002 | 50 mA | | |
| KA-8004 | 20 mA | | |
| KA-8044 | 20 mA | | |
| | | | |
| KM-8002 | 50 mA | | |
| | | | |
| KR-33L | 20 mA | | |
| KR-33SW | 20 mA | | |
| KR-44SL | 20 mA | | |
| KR-44SW | 20 mA | | |
| KR-1110 | 20 mA | | |
| KR-2120 | 20 mA | | |
| KR-2200 | 10 mA | | |
| KR-2300 | 20 mA | | |
| KR-3130 | 20 mA | | |
| KR-3200 | 20 mA | | |
| KR-4050 | 20 mA | | |
| KR-4130 | 20 mA | | |
| KR-4140 | 20 mA | | |
| KR-4200 | 20 mA | | |
| KR-5150 | 30 mA | | |
| KR-5170 | 15 mA | | |
| KR-5200 | 20 mA | | |
| KR-5340 | 20 mA | | |
| KR-6140 | 20 mA | | |
| KR-6160 | 20 mA | | |
| KR-6170 | 30 mA | | |
| KR-6200 | 20 mA | | |
| KR-6340 | 20 mA | | |
| KR-7200 | 20 mA | | |
| KR-7340 | 30 mA | | |
| KR-7070 | 50 mA | | |
| KR-7070A | 50 mA | | |

BIAS-CURRENT VALUE TABLE

| MODEL | BIAS CURRENT | MODEL | BIAS CURRENT |
|----------|--------------|-----------------|--------------|
| KA-1200B | 15 mA | KR-9040 | 25 mA |
| KA-1200G | 15 mA | KR-9060 | — |
| KA-1400B | 20 mA | KR-9400 | 50 mA |
| KA-1400G | 20 mA | KR-9600 | — |
| KA-1500 | 30 mA | KR-9940 | 25 mA |
| KA-1600B | — | KR-10000 | 25 mA |
| KA-1600G | — | KR-10000II | 45 mA |
| KA-3300 | — | | |
| KA-3500 | 40 mA | KS-3000 | 20 mA |
| KA-3550 | 40 mA | | |
| KA-4002A | 20 mA | L-07M | 25 mA |
| KA-4006 | 30 mA | | |
| KA-5500 | 45 mA | MODEL-ELEVEN | 45 mA |
| KA-6006 | 30 mA | MODEL-ELEVEN II | 45 mA |
| KA-7300 | — | MODEL-500 | 25 mA |
| KA-8006 | 30 mA | MODEL-600 | 25 mA |
| KA-8300 | — | MODEL-650 | 25 mA |
| KA-9800 | — | | |
| KE-2500 | — | | |
| KR-1400 | 30 mA | | |
| KR-2400 | 30 mA | | |
| KR-2600 | 25 mA | | |
| KR-3060 | 30 mA | | |
| KR-3400 | 30 mA | | |
| KR-3600 | 30 mA | | |
| KR-3600L | 30 mA | | |
| KR-4400 | 30 mA | | |
| KR-4600 | 40 mA | | |
| KR-5400 | 30 mA | | |
| KR-5600 | 40 mA | | |
| KR-6020 | 30 mA | | |
| KR-6060 | 40 mA | | |
| KR-6400 | 30 mA | | |
| KR-6600 | 40 mA | | |
| KR-7020 | 40 mA | | |
| KR-7060 | 40 mA | | |
| KR-7400 | 40 mA | | |
| KR-7600 | 40 mA | | |
| KR-8040 | 25 mA | | |
| KR-8840 | 25 mA | | |