


Emerson Radio and Phonograph Corp.



MODEL AX-219

L1,	T1	Antenna coil with adjustable 455 kc wave-trap.....
T2		Double-tuned 455 kc first i-f transformer.....
T8		Double-tuned 455 kc second i-f transformer.....
T4		Oscillator coil.....
R1		30,000 ohm $\frac{1}{2}$ watt carbon resistor.....
R2		50,000 ohm $\frac{1}{4}$ watt carbon resistor.....
R3		140 ohm $\frac{1}{2}$ watt wire-wound resistor.....
R4, R17		1 megohm $\frac{1}{4}$ watt carbon resistor.....
R5		Volume control .25 megohm with line switch.....
R6		15 megohm $\frac{1}{4}$ watt carbon resistor.....
R7		250,000 ohm $\frac{1}{4}$ watt carbon resistor.....
R8		500,000 ohm $\frac{1}{4}$ watt carbon resistor.....
R9, R10		Resistance line cord with pilot light ballast section.....
R13		Tone control .5 megohm with motor line switch.....
R14		2,500 ohm 1 watt carbon resistor.....
R15		175 ohm 1 watt metallized resistor.....
R16		100,000 ohm $\frac{1}{4}$ watt carbon resistor.....
R18	C2	Tone control .5 megohm.....
C1, C2		Two-gang variable condenser (for 219 and 221).....
C1, C2		Two-gang variable condenser (for 222 and 232).....
C3		0.00055 mf mica condenser.....
C4		Trimmer, part of wave-trap assembly.....
C5, C11		Trimmers, part of variable condenser.....
C6, C7, C8, C9		Trimmers, part of i-f transformers.....
C10		0.05 mf, 200 volt tubular condenser.....
C12		0.00006 mf mica condenser.....
C18		0.1 mf, 200 volt tubular condenser.....
C14		0.1 mf, 400 volt tubular condenser.....
C15, C18		0.00022 mf mica condenser.....
C16		0.002 mf, 600 volt tubular condenser.....
C17		0.02 mf, 400 volt tubular condenser.....
C19		0.025 mf, 400 volt tubular condenser.....
C20, C21		Dual 20 mf, 150 volt dry electrolytic condenser.....
C22		0.0005 mf mica condenser.....
C23		20 mf, 135 volt dry electrolytic condenser.....
C24		0.01 mf, 400 volt molded condenser.....
C25		0.006 mf, 600 volt tubular condenser.....
C26		0.0008 mf mica condenser.....
		Phono-radio switch.....
		Pilot light, 6.3 volt, .25 amp., Mazda No. 44.....
		Drive cord.....
		Drive cord spring.....
		Drive shaft.....
		Dial face fasteners.....
		Needle cup (for 219 and 221).....
		Needle cup (for 222).....
		Dial pointer (for 221, 222 and 232).....
		Dial crystal (for 221, 222 and 232).....
		Dial face (for 221, 222 and 232).....
		6 $\frac{1}{2}$ " permanent magnet dynamic speaker.....

ADDITIONAL PARTS USED ON AX-219

500,000 ohm $\frac{1}{4}$ watt carbon resistor

ADDITIONAL PARTS USED ON AX-221 and AX-222


1 megohm $\frac{1}{4}$ watt carbon resistor.....

110 volt, a.c. motor (for 221-AC).....

AC-DC motor (for 221AC-DC and 222).....

R11, R12

R11, R12



MODELS AX-221 AC, AX-221 AC-DC and AX-222