

JBL Professional Systems Reference Chart

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
809A	24-14608	45-0107		2416H		842	14053		UREI Coaxial Monitor; L/R
811C	25-15416	45-0113		2425HS		844	14926		UREI Coaxial Monitor; L/R
813C	25-15052	2215H	45-0113	2425HS		843	14926		UREI Coaxial Monitor; L/R
815C	25-15287	2215J (2)	45-0113	2425HS		845	14926		UREI Coaxial Monitor; L/R
2142H		2142H		0175Ti		N2142H			Coaxial Transducer
2152H		2152H		2416H		N2152H	68926		Coaxial Transducer
2155H		2155H		2416H		N2155H	68926		Coaxial Transducer
2901				2410		3101	2301		
2901A				2410		3101	2301		
2901A MI				2461		3101	2301		
2901B				2425J		3101A	2301		
2902				2402 (2)		3102			
2902A				2402 (2)		3102			
2903				2402		3104			
2903A				2402H		3104			
4206	C4206	506G-2S		031TiS		N4206			
4208	C4208	508G-2S		031TiS		N4208			
4301	4510	116A		LE25-2		3103			
4301B	4510B	116H		LE26		3103			
4301BE	4509B	116H		LE26		3103			Built-in amplifier (6001)
4301E	4509	116A		LE25-2		3103			Built-in amplifier (6001E)
4310	4501	123A-1	LE5-2	LE20-1		No Number			
4310 (Late)	4501	2212	2105	LE20-1		3111			
4311	4511	2212	2105	LE25		3112			
4311A	4511-A	2213	LE5-2	LE25		3112A			
4311B	4511B	2213H	LE5-10	LE25-2		3112B			
4312	C4312	2213H	LE5-12	LE25-2		3112C			L,R
4312A	C4312	2213H	104H-3	035Ti		3112D			L,R
4313	4513	LE111A	LE5-9	066		3113			
4313B	4513B	LE10H	LE5-9	066		3113B			
4315	4515	2203A	2108A	2105	2405	3114			Dual bass ports
4315A	4515-1-A	2203A	2108A	2105	2405	3114A			
4315B	4515B	2203H	2108H	2105H	2405	3114A			
4320	4502	2215B		2420		3110	2307	2308	
4325	4505	2216		2420		3122	2307	2308	
4325A	4505A	2216		2420		3122A	2307	2308	
4330	45030	2231A		2420		3130	2312	2308	Bi-amp only
4331	4503-1	2231A		2420		3131	2312	2308	
4331A	4503A-1	2231A		2420		3131A	2312	2308	Switchable for bi-amp

JBL Professional Systems Reference Chart

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
4331B	4503B-1	2231H		2420		3131A	2312	2308	Switchable for bi-amp
4332	4503-2	2231A	2420	2405		3132	2312	2308	Bi-amp only
4333	4503A	2231A	2420	2405		3133	2312	2308	
4333A	4503A-3	2231A	2420	2405		3133A	2312	2308	Switchable for bi-amp
4333B	4503B-3	2231H	2420	2405		3133A	2312	2308	Switchable for bi-amp
4340	4506-1	2231A	2121	2420	2405	3140	2307	2308	Bi-amp only
4341	4506-1	2231A	2121	2420	2405	3141	2307	2308	
4343	4506-3	2231A	2121	2420	2405H	3143	2307	2308	Moveable panel
4343B	4506B	2231H	2121H	2420	2405H	3143	2307	2308	Moveable panel
4344	C4344	2235H	2122H	2426H	2405H	3145	2307	2308	L,R
4345	C4345	2245H	2122H	2425H	2405	3145	2307	2308	L,R
4350	4504	2230 (2)	2202A	2440	2405	3107	2311	2308	Bi-amp only
4350A	4504-A	2231A (2)	2202A	2440	2405	3107	2311	2308	Bi-amp only
4350B	4504-B	2231H (2)	2202H	2440	2405H	3107	2311	2308	Bi-amp only
4355	C4355	2235H (2)	2202H	2441	2405H	3155	2311	2308	Bi-amp only
4375	4575	2105 (4)							
4375A	4575A	LE5-9 (4)							
4380	4580	2110 (4)		2105 (2)		3108	2325		
4380A	4580A	2110 (4)		2105 (2)		3108	2325		
4380B	4580A	2110H (4)		LE5-9 (2)		3108B	2325		
4401	C4401	115H		034		N4401			
4406	C4406	115H-1		035TiA		N4406			
4408	C4408	116H-2		035TiA		N4408			
4410	C4410	127H-1	104H-2	035TiA		N4410			L,R
4411	C4411	128H	LE5-9	044		3109			L,R
4412	C4412	128H-1	104H-2	035Ti		N4412			L,R
4425	C4425	2214H		2416H-1		N3124	2342		L,R
4430	C4430	2235H		2421A		N3134	2344		L,R / Switchable for bi-amp
4430 (Late)	C4430	2235H		2426H		N3134	2344		L,R / Switchable for bi-amp
4435	C4435	2234H (2)		2421A		N3135	2344		L,R / Switchable for bi-amp
4435 (Late)	C4435	2234H (2)		2426H		N3135	2344		L,R / Switchable for bi-amp
4602	4702	K120		2402		3104			
4602A	4702A	E120-8		2402		3104			
4602B	4702A	E120-8		2402H		N4602B			
4604	C4604	E140-8		2425J		N4691	2370A		
4604 (Late)	C4604	E140-8		2426J		N4691	2370A		
4604B	C4604B	E140-8		2425J		N4691	2370A		
4604B (Late)	C4604B	E140-8		2426J		N4691	2370A		
4612	C4612	2118J (2)		2404H-1		N4612			

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
4612B	C4612	2118J (2)		2404H-1		N4612B			
4612OK	C4612OK	2118J (2)		2404H-1		N4612OK			Oak vinyl enclosure
4621	4721	K130							
4621A	4721A	E130-8							
4622	4722	K120 (2)							
4622A	4722A	E120-8 (2)							
4623	4723	E130-8		2402H		3104			
4623B	C4623B	E130-8		2402H		N4602			
4625	4725	E140-8							
4625B	C4625B	E140-8							
4627	4727	E145-8		2410		3103A	2301		
4627A	C4727A	E145-8		2425J		3101A	2301		Switchable for bi-amp
4628	C4628	E145-8	2118H	2404H-1		N4628			
4628B	C4628	E145-8	2118H	2404H-1		N4628			
4638TH	C4648TH	2035HPL(2)				N4638TH			
4641-4	C4641-4	2241G							
4645	C4645	2245H							Use with 5235 and two 51-5138 crossover cards
4646	4512	2204H							
4646A	4512	2206H							
4647	4507	2225H							
4647A	4507	2226H							
4648	4508	2225H (2)							
4648A	C4648A	2226H (2)							
4648-8	4508	2225H (2)							
4648A-8	C4648A	2226J (2)							
4648TH	C4648TH	2226H (2)				N4648TH			HF outputs for 2425H
4660	C4660	2225H		2425J		N4660	65120		
4660 (Late)	C4660	2225H		2426J		N4660	65120		
4660A	C4660	2226H		2426J		N4660			Optional horn grille, G4660
4662	4560BKA	K130		2461		3110	2345		
4662A	4560BKA	E140-8		2425J		3110A	2370		
4662A (Late)	4560BKA	E140-8		2426J		3110A	2370		
4663	4560BKA	K130		2461	2405	3110 & 3106	2345		With 2504 Bracket
4663A	4560BKA	E140-8		2425J	2405H	3110A & 3105	2370		With 2504 Bracket
4663A (Late)	4560BKA	E140-8		2426J	2405H	3110A & 3105	2370		With 2504 Bracket
4670	4508	E145-16 (2)		2441		3152A	2390		
4670 (Late)	4508	2225J (2)		2441		3152A	2390		
4670A	4508	2225J (2)		2445J		3152A	2380		

JBL Professional Systems Reference Chart

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
4670B	4508	2225H (2)		2445J		3160	2380A		
4670C-HF				2445H			2380A		Horn/Driver combination for use w/LF unit
4670D-HF				2446H			2380A		Horn/Driver combination for use w/LF unit
4671	4507	2225H		2425J		N4671	2370A		
4671 (Late)	4507	2225H		2426J		N4671	2370A		
4671OK	4671OK	2225H		2426J		N4671	2370A		
4671OKA	4671OK	2226H		2426J		N4671	2370A		
4672	4560BKA	E145-8		2410		3110	2345		
4672 (Late)	4560BKA	2225H		2410		3110	2345		
4672A	4560BKA	2225H		2425J		3110A	2370A		
4672A (Late)	4560BKA	2225H		2426J		3110A	2370A		
4673	4507	2225H		2445J		3115A	2380		
4674	4560BKA	E145-8		2441		3115	2350		Uses 2328 throat
4674 (Late)	4560BKA	2225H		2441		3115	2350		Uses 2328 throat
4674A	4560BKA	2225H		2445J		3115A	2380A		
4675	4508	2225J (2)		2445J		3152A	2360A		With 2506 bracket
4675A	4508	2225H (2)		2445J		3160	2360A		With 2506 bracket
4675A-2	4508	2225J (4)		2445J (2)		3160	2360A		With 2506 bracket
4675A-4LF	4508	2225H (2)		2445J		3160	2360A		With 2506 bracket
4675A-8LF	4508	2225J (2)		2445J		3160	2360A		With 2506 bracket
4675B-HF				2445H			2360A		Horn/Driver combination for use w/LF unit
4675C-HF				2446H			2380A		Horn/Driver combination for use w/LF unit
4676-1	4550BKA	E145-8 (2)		2441		3152A	2350		Uses 2328 throat
4676-1 (Late)	4550BKA	2225H (2)		2441		3152A	2350		Uses 2328 throat
4676-2	4550BKA (2)	E145-8 (4)		2441 (2)		3152A	2350		Uses 2329 dual throat & 9375 transformer
4676-2 (Late)	4550BKA (2)	2225H (4)		2441 (2)		3152A	2350		Uses 2329 dual throat & 9375 transformer
4676A-1	4550BKA	2225J (2)		2445J		3152A	2360A		With 2506 bracket
4676A-2	4550BKA (2)	2225J (4)		2445J (2)		3152A	2360A		With 2506 bracket (2) & 9375 transformer
4676B-1	4550BKA	2225H (2)		2445J		3160	2360A		With 2506 bracket
4676B-2	4550BKA	2225J (4)		2445J (2)		3160	2365A		With 2506 bracket (2) & 9375 transformer
4680	4780	K110 (4)		2404 (2)		3102			
4680A	4780	E110-8 (4)		2402 (2)		3102			
4680B	C4680B	E110-8 (4)		2402H (2)		3102			
4681	4781	K110 (4)							Molded Enclosure
4682	4782	K110 (4)		2402 (2)		3102			Molded Enclosure
4690	4790	E140-8		2410		3101A	2306		
4690A	4790	E140-8		2425J		3101A	2306		
4691	C4691	E140-8		2425J		N4691	2370		
4691B	C4691B	E140-8		2425J		N4691	2370A		

JBL Professional Systems Reference Chart

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
4691B (Late)	C4691B	E140-8		2426J		N4691	2370A		
4695	4795	E155							
4695B	C4695B	E155-8							
4695B-4	C4695B-4	E155-4							
4698	C4698	E155-4	E110-8	2404H-1		N4698			
4698B	C4698B	E155-4	E110-8	2404H-1		N4698			
4699	C4699	E155-4	E110-8	2425H		N4699	2370A		
4699B	C4699B	E155-4	E110-8	2426H		N4699	2370A		
4716A	C4716	2123H		2416H		N4716A	2342		Neutrik NL4M Input
4726	C4726	2204H		2426J		N4726	2344		Cannon EP-8 Input
4726P	C4726	2204H		2426J		N4726P	2344		XLR Input
4726A	C4726A	2206H		2426J		N4726A	2344		Neutrik NL8 Input
4726AP	C4726A	2206H		2426J		N4726AP	2344		Neutrik NL4 Input
4728	C4728	2204H		2426J		N4728	2344A		Cannon EP-8 Input
4728P	C4728	2204H		2426J		N4728P	2344A		XLR Input
4728A	C4728A	2206H		2426J		N4728A	2344A		Neutrik NL8 Input
4728AP	C4728A	2206H		2426J		N4728AP	2344A		Neutrik NL4 Input
4730A	C4730A	2226H	2118H	2404H		N4730A			Neutrik NL4 Input
4731A	C4731A	2226H		2426J		N4731A	2370		Neutrik NL4 Input
4742	C4742	2204H (2)							XLR Input
4742A	C4742A	2206H (2)							Neutrik NL4 Input
4745	C4745	2225H (2)							XLR or Cannon EP-8 Input
4745A	C4745A	2226H (2)							Neutrik NL8 Input
4748	C4748	2240H							Cannon EP-8 Input
4748A	C4748A	2241H							Neutrik NL8 Input
4750	C4750	2204H (2)		2445J		N4750	2380A		Cannon EP-8 Input
4750P	C4750	2204H (2)		2445J		N4750P	2380A		Cannon EP-8 Input
4750A	C4750	2206H (2)		2445J		N4750A			Neutrik NL8 Input
4750AP	C4750	2206H (2)		2445J		N4750AP			Neutrik NL8 Input
4755	C4755	2204H (2)		2445H		N4755	2480A		Cannon EP-8 Input
4755P	C4755	2204H (2)		2445H		N4755P	2480A		Cannon EP-8 Input
4755A	C4755	2206H (2)		2445J		N4755A	2480A		Neutrik NL8 Input
4755AP	C4755	2206H (2)		2445J		N4755AP	2480A		Neutrik NL8 Input
4770	C4770	2225H (2)		2445J		N4770	2380A		Cannon EP-8 Input
4770P	C4770	2225H (2)		2445J		N4770P	2380A		Cannon EP-8 Input
4770A	C4770	2226H (2)		2445J		N4770A	2380A		Neutrik NL8 Input
4770AP	C4770	2226H (2)		2445J		N4770AP	2380A		Neutrik NL8 Input
4782	C4782	2204H (2)							XLR Input
4782A	C4782A	2206H(2)							Neutrik NL4 Input

JBL Professional Systems Reference Chart

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
4785	C4785	2225H (2)							XLR or Cannon EP-8 Input
4785A	C4785A	2225H (2)							Neutrik NL8 Input
4788	C4788	2240H (2)							XLR or Cannon EP-8 Input
4788A	C4788A	2240H (2)							Neutrik NL8 Input
4825	C4825	2204H		2426J		Bi-amp	2344		Concert Series - Modified horn
4828	C4828	2204H		2426J		Bi-amp	2344		Concert Series - Modified horn
4842	C4842	2245H (2)							Concert Series
4845	C4845	2245H							Concert Series
4847	C4847	2225H							Concert Series
4850	C4850	2204H (2)		2445J		Bi-amp	2380A		Concert Series
4851	C4850	2204H (2)	2445J	2404H (2)		Tri-amp	2380A		Concert Series
4852	C4850	2204H (2)		2445J		Bi-amp	2385A		Concert Series
4853	C4850	2204H (2)	2445J	2404H (2)		Tri-amp	2385A		Concert Series
4860	C4860			2445J			2380A		Concert Series
4861	C4860		2445J	2404H (2)			2380A		Concert Series
4862	C4860			2445J			2385A		Concert Series
4863	C4860		2445J	2404H (2)			2385A		Concert Series
4866	C4866		2445J (2)				2386A		Concert Series
4870	C4870	2225H (2)		2445J		Bi-amp	2380A		Concert Series
4871	C4870	2225H (2)	2445J	2404H (2)		Tri-amp	2380A		Concert Series
4872	C4870	2225H (2)		2445J		Bi-amp	2385A		Concert Series
4873	C4870	2225H (2)	2445J	2404H (2)		Tri-amp	2385A		Concert Series
4892	C4892	1400Pro		2450SL			4892		Array Series; Neutrik NL4 Input
4892-90	C4892	1400Pro		2450SL			2332		Array Series; Neutrik NL4 Input; 90° Horn
4893	C4893	1400Pro (2)							Array Series; Neutrik NL8 Input
4894	C4894	1400Pro (2)		2450SL			4894		Array Series; Neutrik NL8 Input
4894-90	C4894	1400Pro (2)		2450SL			2332		Array Series; Neutrik NL8 Input; 90° Horn
8216	C216BK	306G-2		010		N8216			Black Enclosure
8216A	C8216A	306G-3		TLX012		N8216A			Black Enclosure
8216AT	C8216AT	306G-3		TLX012		N8216AT			Black Enclosure with 15W transformer
8305P2		305G-3A		029Ti		N8305P2			In-wall Installation
8306P2		506G-1		029Ti		N8306P2			In-wall Installation
8325	C8325	310G-2	305G-3	011		N8325			Black Enclosure
8325A	C8325A	310G-3	305G-3	TLX012		N8325A			Black Enclosure
8330	C8330	308G-3	305G-3	TLX012		N8330			Surround / Foreground System
CD5518	CD5518-01	2241G							
CD5525	CD5525-01	2206H		2416H-1		CD5525-02	2373		
Control 1	C1001	C1003		C1022		C1006			Serial no's through 0510210184
Control 1 (Late)	C1001	C1003		C1002		C1006			Serial no's from 0510210185

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
Control 1AT	C1001AT	C1003AT		C1002AT		C1006AT			Line distribution version of Control 1 All-weather version of Control 1AT Ceiling-mount version of Control 1AT Serial no's through 0510210184 Serial no's from 0510210185
Control 1AW	C1001AW	C1003AW		C1002AW		C1006AW			
Control 1CM	C1001CM	C1003CM		C1002CM		C1006CM			
Control 1 Plus	C1001P	C1003P		C1022P		C1006P			
Control 1 Plus	C1001P	C1003P		C1002P		C1006P			
Control 5	C5001	C5003		C5002		C5006			
Control 10	69478-01	69493	305HS	037TiS		70605-8		L,R	
Control 10-A	C10	119HS-1	305HS	037TiS		N10-A		L,R	
Control 12SR-A	C12SR	G125B-8		2416H		N12SR	2372		
Control Micro	71147-01	304GS				NCMicro			
Control SB-1	CSB-1	CSB-1003(4)				NCSB-1		Use w/ Control SB Micro Subwoofer	
Control SB-5	CSB-5	CSB-5003(4)				NCSB-5			
Control SB Micro	CSB Micro	308SW				NCSB Micro		Use w/Control Micro Satellites	
G-718	CG-718	E155-4				NG-718			
G-730	CG-730	G125A-8		2416H		NG-730	2371		
G-731	CG-731	G125A-8		2416H-1		NG-731	2371		
G-732	CG-732	G135A-8		2416H		NG-732	2371		
G-733	CG-733	MI10-1	2118J-1	2416H		NG-733	2371		
G-734	CG-734	G135A-8		2416H		NG-734	2371		
G-791				2416H		NG-791	2371	Horn/Driver combination for use w/LF unit	
J316Pro	CJ316PRO	506GS		020Nd		NJ316PRO			
M330	CM330	M222-8		2416HPL		NM330	2371		
M350	CM350	M252-8		2416HPL		NM350	2371		
M360	CM360	M252-8	M209-8	M202A		NM360			
MI-261	CMI-261			2415H		NMI-261	2371		
MI-291				2415H		NMI-291	2371	Horn/Driver combination for use w/LF unit	
MI-630	CMI-630	MI-12-1		2415H		NMI-630	2371		
MI-631	CMI-631	MI-12-1		2415H		NMI-631	2371		
MI-632	CMI-632	MI-15		2415H		NMI-632	2371		
MI-632A	CMI-632	MI-15A		2415H		NMI-632	2371		
MI-634	CMI-634	MI-15A		2415H		NMI-634	2371		
MR802	CMR802	2022H		2416H-1		NMR802	2373		
MR805	CMR805	2032H		2416H-1		NMR805	2373		
MR812	CMR812	M121-8				NMR812			
MR815	CMR815	M151-8				NMR815			
MR818	CMR818	2042H				NMR818			
MR822	CMR822	2022H		2416H-1		NMR822	2373		
MR825	CMR825	2032H		2416H-1		NMR825	2373		
MR826	CMR826	2032H		2416H-1		NMR826	2373		

JBL Professional Systems Reference Chart

Model	Enclosure	Low Freq	Mid Freq	High Freq	Ultra-High Freq	Network	Horn	Lens	Notes
MR835	CMR835	2032H	2118H	2416H-1		NMR835	2373		
MR838	CMR838	2042H	MI10-1	2416H-1		NMR838	2373		
SLT-1	CLT-1	62861		024		NLT-1			LF is integral part of baffle
SR4704	CSR4704	2226H		2426H		NSR4704	2370A		Switchable for bi-amp
SR4704A	CSR4704A	2226H		2426H		NSR4704A	2370A		Switchable for bi-amp- 1/4 or Neutrik Input
SR4706A	CSR4706A	2226G		2447J		NSR4706A	2383		Switchable for bi-amp- 1/4 or Neutrik Input
SR4715A	CSR4715A	2226H (2)				NSR4715A			1/4" or Neutrik Input
SR4715N	CSR4715N	2226H (2)				NSR4715N			Neutrik NL4 Input
SR4718	CSR4718	2241G				NSR4718			
SR4718A	CSR4718A	2241H				NSR4718A			1/4" or Neutrik Input
SR4719A	CSR4719A	2241H (2)				NSR4719A			1/4" or Neutrik Input
SR4722	CSR4722	2206H		2416H-1		NSR4722	2342		Switchable for bi-amp
SR4722A	CSR4722A	2206H		2417H		NSR4722A	2342		Switchable for bi-amp- 1/4 or Neutrik Input
SR4725	CSR4725	2226H		2426H		NSR4725	2370A		Switchable for bi-amp
SR4725A	CSR4725A	2226H		2426H		NSR4725A	2370A		Switchable for bi-amp- 1/4 or Neutrik Input
SR4726A	CSR4726A	2226G		2447J		NSR4726A	2381		Switchable for bi-amp- 1/4 or Neutrik Input
SR4731A	CSR4731A	2206H (2)		2447J		NSR4731A	2381		Switchable for bi-amp- 1/4 or Neutrik Input
SR4732	CSR4732	2206H (2)	2445J	2404H-1		NSR4732	2380A		Switchable for bi-amp
SR4732A	CSR4732A	2206H (2)	2447J	2404H-1		NSR4732A	2381		Switchable for bi-amp- 1/4 or Neutrik Input
SR4732AT	CSR4732AT	2206H (2)	2447J	2404H-1		NSR4732AT	2381		Tri-amp only - 1/4" or Neutrik Input
SR4732N	CSR4732	2206H (2)	2445J	2404H-1		NSR4732N	2380A		Neutrik NL8 Input
SR4733A	CSR4733A	2226H (2)		2447J		NSR4733A	2381		Switchable for bi-amp- 1/4 or Neutrik Input
SR4735	CSR4735	2226H	2118H	2416H-1		NSR4735	2371		Switchable for bi-amp
SR4735A	CSR4735A	2226H	2119H	2417H		NSR4735A	2371		Switchable for bi-amp- 1/4 or Neutrik Input
SR4738	CSR4738	2241G	2123H	2416H-1		NSR4738	2371		Switchable for bi-amp
SR4738A	CSR4738A	2241G	2123H	2417H		NSR4738A	2371		Switchable for bi-amp- 1/4 or Neutrik Input