


Westinghouse CHASSIS ASSEMBLY V-2189-2

MODELS H-434T5 H-435T5 H-436T5 H-437T5 H-438T5



ALIGNMENT

Step	Connect Signal Generator to—	Signal Generator Frequency	Radio Dial	Adjust for Maximum Output —
1.	Stator of ant. tuning capacitor (A) through a 200 mmf capacitor	455 kc.	Minimum capacity	Top and bottom slugs of T2 and T1 in order given
2.	Same as Step 1	1625 kc.	Minimum capacity	Oscillator trimmer (D)
3.	Radiated signal	1400 kc.	1400 kc.	Antenna trimmer (B)

