

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
033	034	Yes	No	(2)	Not safe for L40 or L110 systems
066	044	Yes	Yes	(2)	
075	2402H	Yes	No	(1)	
075R	2402H	Yes	No	(2)	
076	2405H	Yes	No	(3)	Altered dispersion characteristics
077	2405H	Yes	No	(1)	
112A	108H	Yes	No	(3)	Requires extensive network modification for L212 use
112H	108H	Yes	No	(3)	Requires extensive network modification for L212 use
116A	116H	Yes	No	(2)	
117H	117H-1	Yes	No	(1)	
121A	None				B212 Only
121H	None				B212 Only
122A	128H-1	Yes	No	(3)	
122A-1	128H-1	Yes	No	(3)	
123A	2213H	Yes	No	(2)	Reverse polarity
123A-1	2213H	Yes	No	(2)	Reverse polarity
123A-2	2213H	Yes	No	(2)	Reverse polarity
123A-3	2213H	Yes	No	(2)	
124A	128H-1	Yes	No	(3)	Or LE14H-1 with baffle modification
124H	128H-1	Yes	No	(3)	Or LE14H-1 with baffle modification
125A	118H	Yes	No	(2)	
126A	128H-1	Yes	No	(2)	
127A	118H	Yes	No	(2)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
127H	118H	Yes	No	(2)	
128H	128H-1	Yes	No	(1)	
129H	128H-1	Yes	No	(1)	
130A	2220H	Yes	No	(2)	
130B	2220J	Yes	No	(2)	
130H	2220H	Yes	No	(2)	
135A	2235H	Yes	No	(2)	
136A	2235H	Yes	No	(2)	
136B	2235H	Yes	No	(2)	
136H	2235H	Yes	No	(2)	
150-4	E145-8	Yes	No	(2)	
150-4C	E145-8	Yes	No	(2)	
150H	2234H	Yes	No	(3)	
275	2425J	Yes	No	(2)	
303G	303G-2	Yes	No	(2)	
303G-1	303G-2	Yes	No	(2)	
305G	305G-2	Yes	No	(2)	
305G-1	305G-2	Yes	No	(2)	
308G	308G-2	Yes	No	(2)	
308G-1	308G-2	Yes	No	(2)	
310G	310G-2	Yes	No	(2)	
310G-1	310G-2	Yes	No	(2)	
312G	312G-1	Yes	No	(2)	
375	2441	Yes	No	(2)	
375H	None				
376	2441	Yes	No	(1)	
2105	2105H	Yes	No	(2)	
2108	2118H	Yes	No	(2)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
2108H	2118H	Yes	No	(2)	
2110	2118H	Yes	No	(2)	
2110H	2118H	Yes	No	(2)	
2115	LE8T-H	Yes	No	(3)	Or 2118 with baffle modification
2115A	LE8T-H	Yes	No	(3)	Or 2118 with baffle modification
2115B	LE8T-H	Yes	No	(3)	Or 2118 with baffle modification
2115H	LE8T-H	Yes	No	(3)	Or 2118 with baffle modification
2115J	LE8T-H	Yes	No	(3)	Or 2118 with baffle modification
2120	E110-8	Yes	No	(2)	
2121	2122H	Yes	No	(2)	
2121H	2122H	Yes	No	(2)	
2125	2213H	Yes	No	(3)	
2130	E120-8	Yes	No	(2)	
2135	E130-8	Yes	No	(2)	
2145	None				Must be replaced with a 2-way system
2150	None				Or 2118 with baffle modification
2202A	2202H	Yes	No	(2)	
2202B	2202H	Yes	No	(2)	
2202J	2202H	No	No	(2)	
2203A	128H-1	Yes	No	(3)	Or LE14H-1 with baffle

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
					modification
2203H	128H-1	Yes	No	(3)	
2205A	2225H	Yes	No	(2)	
2205B	2225J	Yes	No	(2)	
2205C	2225J	Yes	No	(2)	
2205H	2225H	No	No	(2)	
2205J	2225J	No	No	(2)	
2212	2213H	Yes	No	(2)	
2213	2213H	Yes	No	(2)	
2215	2234H	Yes	No	(3)	
2215A	2234H	Yes	No	(3)	
2215B	2234H	Yes	No	(3)	
2215H	2234H	Yes	No	(3)	
2216	2234H	Yes	No	(3)	
2220A	2220H	Yes	No	(2)	
2220B	2220J	Yes	No	(2)	
2220C	2220J	Yes	No	(2)	
2230A	2235H	Yes	No	(2)	
2231A	2235H	Yes	No	(2)	
2231H	2235H	No	No	(2)	
2290	None				
2295	None				
2402	2402H	Yes	No	(2)	
2403	2405H	Yes	No	(3)	Altered dispersion characteristics
2405	2405H	Yes	No	(2)	
2410	2425J	Yes	No	(2)	
2420	2425J	Yes	No	(2)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
2421	2425J	Yes	No	(2)	
2440	2441	No	No	(2)	Do not use the 2441 in the 4350 series without network modification
2441	2445J	Yes	Yes	(2)	
2460	2425J	Yes	No	(2)	
2461	2425J	Yes	No	(2)	
2470	2425J	Yes	No	(2)	
2480	2482	No	No	(2)	
2482	2445J	No	Yes	(2)	
D15S	E130-8	Yes	No	(2)	
D110F	E110-8	Yes	No	(2)	
D110F-6	E110-16	Yes	No	(2)	
D120	E120-8	Yes	No	(2)	
D120F	E120-8	Yes	No	(2)	
D120F-2	E120-8	Yes	No	(2)	
D120F-6	E120-16	Yes	No	(2)	
D123	E120-8	Yes	No	(2)	Reverse polarity
D123-3	E120-8	Yes	No	(2)	
D123F	E120-8	Yes	No	(2)	Reverse polarity
D130	E130-8	Yes	No	(2)	
D130F	E130-8	Yes	No	(2)	
D130F-2	E130-8	Yes	No	(2)	
D130F-6	E130-16	Yes	No	(2)	
D130H	E130-8	Yes	No	(2)	
D131	E120-8	Yes	No	(2)	
D131F	E120-8	Yes	No	(2)	
D140F	E140-8	Yes	No	(2)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
D140F-2	E140-8	Yes	No	(2)	
D140F-6	E140-16	Yes	No	(2)	
D175	2425J	Yes	No	(2)	
D204	2118H	Yes	No	(2)	Reverse polarity
D208	2118H	Yes	No	(2)	Reverse polarity
D208H	2118H	Yes	No	(2)	Reverse polarity
D216	2118H	Yes	No	(2)	Reverse polarity
D260	2118H	Yes	No	(2)	Reverse polarity
D280	2118H	Yes	No	(2)	
E130-4	E130-8	No	No	(1)	
E151-8	E155-8	Yes	No	(2)	
HL180	2425J	Yes	No	(2)	
K110	E110-8	Yes	No	(2)	
K110-4	E110-8	Yes	No	(2)	
K110-16	E110-16	Yes	No	(2)	
K120	E120-8	Yes	No	(2)	
K120-4	E120-8	Yes	No	(2)	
K120-6	E120-16	Yes	No	(2)	
K120-16	E120-16	Yes	No	(2)	
K130	E130-8	Yes	No	(2)	
K130-4	E130-8	Yes	No	(2)	
K130-16	E130-16	Yes	No	(2)	
K140	E140-8	Yes	No	(2)	
K140-4	E140-8	Yes	No	(2)	
K140-16	E140-16	Yes	No	(2)	
K145	E145-8	Yes	No	(2)	
K145-4	E145-8	Yes	No	(2)	
K145-16	E145-16	Yes	No	(2)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
K151	E155-8	Yes	No	(2)	
K151-4	E155-8	Yes	No	(2)	
K151-16	E155-16	Yes	No	(2)	
LE5-2	LE5-9	Yes	No	(2)	
LE5-3	LE5-9	Yes	No	(2)	
LE5-6	LE5-12	Yes	No	(1)	
LE5-8	LE5-12	No	No	(1)	
LE5-10	LE5-12	Yes	No	(1)	
LE5H	LE5-9	No	No	(1)	
LE8	LE8T-H	Yes	No	(2)	
LE8-1	LE8T-H	Yes	No	(2)	
LE8-7	None				Passive radiator
LE8T	LE8T-H	Yes	No	(2)	
LE8T-2	LE8T-H	Yes	No	(3)	
LE8TX	LE8T-H	Yes	No	(3)	
LE10A	LE10H-1	Yes	No	(2)	
LE10B	LE10H-1	Yes	No	(2)	
LE10H	LE10H-1	Yes	No	(1)	
LE12C	None				Must be replaced with a 2-way system
LE14A	LE14H-1	Yes	No	(2)	
LE14A-2	LE14H-1	Yes	No	(2)	
LE14C	None				Must be replaced with a 2-way system
LE14H	LE14H-1	Yes	No	(2)	
LE15A	2234H	Yes	No	(3)	
LE15B	2234H	Yes	No	(3)	
LE15H	2234H	Yes	No	(3)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.

JBL TRANSDUCER REPLACEMENT LIST

Transducer Model	Acoustic Equivalent	Visual Change	Baffle Modification	Category	Notes
LE20	LE25-2	Yes	Yes	(3)	
LE20-1	LE25-2	Yes	Yes	(3)	
LE21H	LE25-2	Yes	No	(2)	
LE25	LE25-2	Yes	No	(2)	
LE25-1	LE25-2	Yes	No	(2)	
LE25-3	LE25-2	Yes	No	(2)	
LE25-4	LE25-2	Yes	No	(2)	
LE25-5	LE25-2	Yes	No	(2)	
LE30	LE25-2	Yes	Yes	(3)	
LE75	2425J	Yes	No	(2)	
LE85	2425J	Yes	No	(2)	
LE100S	2425J	Yes	No	(2)	
LE111A	LE10H-1	Yes	No	(3)	
LE111H	LE10H-1	Yes	No	(1)	
LE175	2425J	Yes	No	(2)	
PR8	None				Passive radiator
PR10	None				Passive radiator
PR10F	None				Passive radiator
PR12	PR300	Yes	No	(2)	Requires tuning
PR14	None				Passive radiator
PR15	None				
PR15C	None				
PR15D	None				
PR15F	None				
PR15R	None				
PR300	PR310-1	Yes	No	(2)	
PR310	PR310-2	Yes	No	(2)	
PR310-1	PR310-2	Yes	No	(2)	

JBL TRANSDUCER REPLACEMENT LIST EXPLANATIONS

This is a listing of replacement transducers to be used when the original driver is missing or cannot be repaired.

Replacement transducers fall into the following categories:

1. Exact acoustic replacement.
2. Slightly different (usually improved) replacement.
3. Last resort.

*Both units in a stereo pair should be changed when using category 2 and 3 replacements.

*Considering the age of transducer to be replaced, category 1 replacements may also require changing both units of a stereo pair for best performance.

*Impedance changes have not been noted.