
SCHEMATIC DIAGRAM



STROMBERG-CARLSON NOS. 635 AND 636 RECEIVERS

The following table shows how the filament, plate and grid voltages vary with different line voltages, in the No. 635 receiver. The plate voltages are measured between tube plates and Tap No. 2 of the voltage divider. The grid voltages of the heater type tubes are measured across the cathode resistors; and that of the audio output tube is measured between Taps No. 1 and No. 2 of the voltage divider.

Line Voltage	105	110	115	115	120	125
"HI-LO" Switch	"LO"	"LO"	"LO"	"HI"	"HI"	"HI"
UX-280 Filament Voltage (RMS) Voltage per anode (RMS)	4.5 236.0	4.75 248.0	5.0 2 59.0	4.5 23 6.0	4.7 248.0	4.93 258.0
Amplifiers Heater Voltage (RMS) Plate Voltage Grid Voltage	2.17	2.27	2.38	2.16	2.26	2.35
	106.0	110.0	115.0	106.0	110.0	115.0
	— 5.0	— 5.5	— 5.75	4.7	— 5.2	— 5.6
Detector Heater Voltage (RMS) Plate Voltage Grid Voltage	2.11	2.22	2.32	2.1	2.2	2.3
	39.0	40.0	42.0	38.0	40.0	41.0
	— 3.25	— 3.5	— 3.75	3.25	— 3.5	— 3.75
Audio Output Tube Filament Voltage (RMS) Plate Voltage Grid Voltage	4.5 167.0 —37.0	4.75 175.0 —40.0	5.0 184.0 —41.0	4.53 165.0 —36.0	4. 72 174.0 —40.0	4.94 182.0 —41.0

NOTE—The grid voltage on the 1st audio tube will be slightly lower than that on the R. F. amplifier tubes, due to the drop in the secondary of the 1st audio transformer.