




CHASSIS 6L03



Operation	Connect Oscillator To	Dummy Antenna	Input Sig. Frequency	Set Dial At	Trimmers	Purpose
1	Converter Grid	.5 Mfd.	455 Kc.	600 Kc.	L4,L5,L6, L7	For I.F. Alignment.
2	One Turn Loop Coupled Loosely to Wave-magnet	_____	1600 Kc.	1600 Kc.	C1F	Set Oscillator to Dial Scale.
3		_____	1400 Kc.	1400 Kc.	C1D, C1B	Align Detector and Antenna Stage.