

In honor of our 75th anniversary, JBL has crafted the SA750 integrated amplifier with retro styling, commemorative badging, vintage teak-wood veneer side panels, and thoroughly modern features, connectivity, and amplification. The SA750 is inspired by the classic JBL SA600 amplifier from the '60's, updated with state-of-the-art streaming audio, wireless connectivity, Dirac Live room correction, and Class G amplifier technology.

The SA750 features a high-resolution DAC and has built-in WiFi for streaming music via online services and for streaming over AirPlay 2 and Chromecast from compatible devices. It's also a Roon endpoint. Shipped with a calibration microphone, the SA750 features DIRAC Live to fine-tune the output of speakers and subwoofers to the listening space. Rated at a conservative 120 Watts rms per channel, the Class G amplifier provides Class A performance at low levels and brings in a higher power supply for more demanding dynamics. With four digital and four analog inputs, including MM/MC phono inputs, the SA750 is ready for any audio source. IP control allows for easy smart home integration.

The SA750 is a throw-back to those earlier JBL receivers. But with a modern amber LED display, exceptional dynamic range and connectivity, the SA750 is a modern classic rooted in today's best technologies. Designed to complement the 75th Anniversary Edition L100 Classic 75.



Highlights:

- Retro-styled integrated amplifier with modern features
- · High-resolution Google Cast, AirPlay 2, uPnP Streamer
- · Class-leading Class G amplifier topology
- DIRAC Live room correction
- Roon endpoint; MQA supported
- Full IP control including Control4 and Crestron
- Power output 120W per channel into 8Ω , 220W into 4Ω
- 4 digital and 5 analog inputs including MM/MC Phonograph input
- Compatible with the MusicLife app
- Vintage teak-wood veneer side panels match 75th Anniversary Edition L100 Classic 75

General Specifications:

- ► Frequency Response: 20Hz 20kHz ± 1dB
- ► Nominal Sensitivity: 1V
- Input Impedance: 10kΩ
- ▶ Power output both channels driven: 120W into 8 Ω , 220W into 4 Ω
- ► Maximum Input: 6Vrms
- ► Total harmonic distortion + noise: 0.002%
- ► Signal/Noise ratio (A-wtd) 50W, ref. 1V input: 120dB
- ► Mains Voltage: 110–120V or 220–240V, 50–60Hz
- ► Maximum Power Consumption: 800W
- ► Product Dimensions (W x H x D, including feet, control knob and speaker terminals): 449 x 114 x 327mm
- ► Product Weight: 12kg
- ► Shipping Weight: 14kg
- Warranty: 5 Years

HARMAN International Industries, Incorporated 8500 Balboa Boulevard, Northridge, CA 91329 USA www.jbl.com