

TRIO DELUXE STEREO PRE-MAIN AMPLIFIER

Model W-45A

FEATURES

- 1. The W-45A has a powerful output of 18 watts for each channel and 36 watts for monaural operation.
- 2. Hum is entirely eliminated by the Direct Current Filament Heating System adopted in the equalizer circuit.
- 3. New Type Balance Meter helps quick and accurate balancing between the two channels.
- 4. Rumble Filter completely eliminates annoying low level disturbance.
- 5. Loudness Control assures realism such as experienced only at concert halls, even when volume is set at a low level.
- 6. Clutch Type Tone Controls adjust tone separately or simultaneously.
- 7. Stereo head-phone can be connected.
- 8. Speaker Phasing Switch brings right and left speakers back into phasing position, if speakers are connected out of phase.

SPECIFICATIONS

Tubes Used: 12AX7 x 4, 12AU7 x 2, 6BQ5 x 4, 5AR4, OA-79 x 2, total, 13 tubes.

Output Power: 18W x 2 (harmonic distortion less than 1%) monaural, 36W.

Frequency Response: ± 1 dB 20-40,000.

Input: Mag: 15 W with input of 3 mV. Tape HD: 15 W with input of 4 mV. Tuner: 15 W with input of 145 mV. Aux: 15 W with input of 145 mV.

Tone Control: 50 c/s, + 13 dB — 12.5 dB; 10 Kc, + 13 dB — 16 dB.

Loudness Control: 50 c/s + 16 dB, 10 Kc + 2.5 dB with volume control at — 30 dB.

Equalizer: RIAA (LP record) NARTB (tape recorder).

Residual Noise: 2.0 mV (Aux) 30 mV (Mag) 20 mV (Tape HD) maximum volume, tone control flat.

Output Terminals: 4, 8, 16 ohms (pair of each).


LEFT


Special Circuit: Balance Meter, Rumble Filter, Loudness Control.

Power Source: 250 V, 50-60 c/s.

Dimensions: Width 15%"; Height 5%"; Depth 11%".

Weight: 24 lbs.






Sole Australian Importers & Distributors

BARDSLEY IMPORT TRADING CO.

• 166d GLEBE ROAD, GLEBE, N.S.W. PHONES MW 1453 - MW 4283 •

ARROW ELECTRONICS

422 Kent Street SYDNEY



W - 45

AMPLIFICATORE STEREOFONICO PROFESSIONALE



10-30.000 cps. \pm 1 dB - 18 + 18 watt (12 + 12 indistorti) su 4, 8, 16 ohm - Sensibilità 2 mV FONO, 2 mV TESTINA NASTRO, 150 mV RADIO e AUSIL. - Comando Bassi e Acuti (\pm 15 dB) indipendenti sui due canali - Compensazione fisiologica - Presa Cuffia - Filtro antirombo - Strumento di controlo della potenza emessa e del bilanciamento - Ronzio —90 dB 20 funzioni di valvola - Dimensioni mm 390 \times 135 \times 300.

Prezzo Listino Lit. 140.000